

Welcome to Teensy++

With C Language

Programming Teensy++ with C provides access to all features. Experience with the C language and reading technical specifications is helpful. For a beginner oriented environment, Arduino may be a better

To begin using Teensy++ with C, please visit the website and click Getting Started.

<http://www.pjrc.com/teensy>

Pin Assignments Using C Language

	GND				Vcc				
OC1C	OC0A	PB7			PB6	OC1B			
SCL	OC0B	INT0	PD0		PB5	OC1A			
SDA	OC2B	INT1	PD1		PB4	OC2A			
RXD1	INT2	PD2			PB3	MISO			
TXD1	INT3	PD3			PB2	MOSI			
	ICP1	PD4			PB1	SCLK			
	XCK1	PD5			PB0	SS			
(LED on PD6)	T1	PD6			PE7	INT7	AIN1		
	T0	PD7			PE6	INT6	AIN0		
		PE0			GND				
		PE1			AREF				
(interior)		PC0			PF0	ADC0	(interior)		
PA4	PA0	PC1			PF1	ADC1	PE4	INT4	TOSC1
PA5	PA1	PC2			PF2	ADC2	PE5	INT5	TOSC2
PA6	PA2	T3	PC3		PF3	ADC3			
PA7	PA3	OC3C	PC4		PF4	ADC4			
ALE		OC3B	PC5		PF5	ADC5			
		OC3A	PC6		PF6	ADC6			(bottom)
		ICP3	PC7		PF7	ADC7			RST

